

Shot Box - Ref. SB-80

Cost effective solution to easily control the Presets on **LiveCore™** and **Midra™** series



Shot Box at a glance

- ▶ 76 function-labeled keys
- ▶ Customizable blue and red backlighting
- ▶ Readily operational on all **LiveCore™** series (External Software supplied)
- ▶ Readily operational on all **Midra™** series (direct control via the RCS² software)
- ▶ USB connection to PC or Mac

Key features

- ▶ **User Controls**
 - 70 keys to load instantly Master presets, Screen presets or Confidence Screen presets (up to 140 presets available for **LiveCore™** series and up to 64 presets available for **Midra™** series)
 - 4 keys for the Customizable Monitoring/Preview (8 presets available: **LiveCore™** series only)
 - 1 large key for the Page selection (**LiveCore™** series only)
 - 1 large key for the Take button
- ▶ **Connectors**
 - 1 USB connector

To Control the following Switchers

LiveCore™ series	Midra™ series
▶ ASC4806-4K: Ascender 48 - 4K*	▶ EKS550: Eikos ²
▶ ASC3204-4K: Ascender 32 - 4K*	▶ SPX450: Saphyr
▶ ASC1602-4K: Ascender 16 - 4K*	▶ SMX250: SmartMatriX ²
▶ SMX12x4: SmartMatriX Ultra	▶ PLS350: Pulse ²
▶ NXT1604: NeXtage 16	▶ PLS350-3G: Pulse ²
▶ NXT0802: NeXtage 08	▶ QMX150: QuickMatriX
*Non-4K units are supported	▶ QVU150: QuickVu
	▶ QVU150-3G: QuickVu

Dimensions:

- ▶ D 7.25" x W 8.25" x H 0.94"
- ▶ D 184 mm x W 210 mm x H 240 mm

Weight:

- ▶ 0,726 kg
- ▶ 1.6 lbs

Supplied with:


- ▶ 1 x Carrying case
- ▶ 1 x USB stick containing both the Windows and MAC OS X setup applications*
- ▶ 1 x Quick Start Guide*

Warranty:

1-year warranty on parts and labor back to factory.


LiveCore™ series

NeXtage 08 Ref. NXT0802	Ascender 16 - 4K Ref. ASC1602-4K
NeXtage 16 Ref. NXT1604	Ascender 32 - 4K Ref. ASC3204-4K
SmartMatriX Ultra Ref. SMX12x4	Ascender 48 - 4K Ref. ASC4806-4K



Midra™ series

Eikos ² Ref. EKS550	Saphyr Ref. SPX450	SmartMatriX ² Ref. SMX250
Pulse ² Ref. PLS350	QuickMatriX Ref. QMX250	QuickVu Ref. QVU150



NOTE

Connect the Shot Box USB cable directly to your computer - Do not connect the Shot Box USB cable to the USB port of your **LiveCore™/Midra™** series.



* The Quick Start Guide and the External Software are also available on www.analogway.com

① Specifications subject to change without prior notice

All technical specifications are available on our website

Follow us

Europe, Middle East and Africa - ANALOG WAY SAS - Tel: +33 (0)1 81 89 08 60 / Fax: +33 (0)1 57 19 04 54 / Email: saleseuro@analogway.com
 The Americas - ANALOG WAY Inc. - Tel: +1 212 269 1902 / Fax: +1 212 269 1943 / Email: salesusa@analogway.com
 Asia Pacific - ANALOG WAY Pte Ltd - Tel: +65 62 92 58 00 / Fax: +65 62 92 52 05 / Email: sales@analogwayasia.com

SB-80-uk-05/10/2016



ANALOG WAY®
Pioneer in Analog. Leader in Digital